

# CØDA

Portable, high-power, ultrasonic instrument

## Equipment Highlights

- Patented pulser technology to pulse both EMAT and piezoelectric sensors
- Non-contact, no-couplant EMAT sensors provide measurements and flaw detection at extreme temperatures from -30° to 650°C
- Works with piezoelectric sensors from any manufacturer and Innerspec's proprietary Dry-Coupled piezoelectric sensors
- Custom EMAT applications for thickness measurement, corrosion mapping, stress measurement (train wheels, rails, plates), bolt-load measurement and 0° flaw detection
- Conventional UT applications for thickness measurement, and shear wave inspection
- NDT-WEB software permits direct control from any connected device using built-in WiFi
- NDT-LINK connectivity for Innerspec's cloud services

CØDA is the first and only compact high-power UT flaw detector capable of working with both EMAT and piezoelectric sensors using Innerspec's patented pulser technology. Available EMAT applications include thickness gauging, corrosion mapping, bolt-load measurement, stress measurement, and flaw detection with normal beam. When fitted with piezoelectric transducers, CØDA works as a conventional UT flaw detector and includes all standard ultrasonic applications including normal beam, shear wave and surface waves.

CØDA+ incorporates a one axis encoder input to be able to plot strip charts and C-scans using a manual or an automated scanner. CØDA SM permits pulsing a custom two-channel EMAT sensor for stress measurement. CØDA is designed to work with EMAT sensors from Innerspec and piezoelectric sensors from any manufacturer.



## CODA – Technical Specifications

|                                   |   |  |
|-----------------------------------|---|--|
| <b>Ultrasonic Pulsers</b>         | 1 - EMAT  | 1 - PIEZO  |
| <b>Bandwidth</b>                  | 1500 kHz to 10 MHz  | 100 kHz to 10 MHz  |
| <b>Pulse Repetition Rate</b>      | Up to 400 Hz  | Up to 400 Hz   |
| <b>RF Pulser</b>                  | 1-3 Cycles (Toneburst)<br>16kW power output<br>800Vpp @ 40Amp pk<br>0.6% maximum duty   | Half Cycle Square Wave<br>600 W power Output<br>100 V - 400 V @ 5Amp pk<br>0.6% maximum duty |
| <b>Receivers</b>                  | 20 dB to 90 dB Gain   | 0 dB to 48 dB Gain   |
| <b>Pulse / Receive Modes</b>      | Pulse-Echo/Pitch-Catch  |  |
| <b>Dual Channel Multiplexer</b>   | Yes (CODA SM)   | No   |
| <b>Analog /Digital Converters</b> | 14-bit, 100 MSPS  |  |
| <b>Rectification</b>              | Full-wave +/- half-wave, Envelope and RF mode   |  |
| <b>Filtering</b>                  | Programmable digital filters  |  |
| <b>Evaluation Gates</b>           | 3 gates per channel<br>Amplitude, time and frequency  |  |
| <b>Encoder Interface</b>          | A/B Quadrature or clock/direction (CODA+, CODA SM)  |  |
| <b>PC Communication</b>           | Wi-Fi 2x802.11ac/ax dual band<br>USB 3.0, Ethernet  |  |
| <b>Software</b>                   | ITOP with NDT-WEB   |  |
| <b>Internal Storage Capacity</b>  | 32 GB SSD   |  |
| <b>Memory</b>                     | 8 GB RAM  |  |
| <b>Probe Connector</b>            | LEMO, BNC, Thermocouple   |  |
| <b>Operating Temperature</b>      | 32°F to 105°F (0°C to 40°C)   |  |
| <b>Power Input</b>                | USB Type-C adapter input: 100-240 VAC, 50-60 Hz   |  |
| <b>Rechargeable Battery</b>       | Li-Ion 14.4V, 49Wh, <10A@ 6.8Ah;<br>up to 10 hours battery life   |  |
| <b>Other I/O</b>                  | HDMI, Thermocouple  |  |
| <b>Temperature Compensation</b>   | Automatic, thermocouple input   |  |
| <b>User Interface</b>             | Portable touchscreen 6.6" (default)<br>Web browser accessible through ITOP operating platform on<br>any operating system and device |  |
| <b>Dimensions</b>                 | 8.8"(W) x 7.2"(D) x 2.6"(H)<br>223 mm(W) x 182 mm(D) x 70 mm(H)   |  |
| <b>Weight</b>                     | 3.49lb/1.58kg (2.97 lb/1.35kg without battery)  |  |

\*AVAILABLE ONLY WITH CODA+ AND CODA STRESS

CODA\_0725