



 PORTABLE	 POWER WHEREVER YOU GO	 LOCATION-READY	+ -	 15KVA	 POWERS ROBOT AND TRACK
--	---	--	------------	---	--

DIMENSIONS

CART POWER CABLE	9' 10"
ROBOT POWER CABLE for C20/C31 (Not included with smart transformer)	22' 11" or 49' 2"
CART DIMENSIONS	51.5" x 50" x 29"
WEIGHT	675 lbs

POWER

PWR INPUT RECEPTACLE	250V 60A (male) IEC 60309 60A 3P 4W
ROBOT POWER OUTPUT RECEPTACLE	480V 20A (female) IEC 60309 20A 3P 4W (x2)
SHORT CIRCUIT CURRENT RATING	5kA
MAX POWER	15kVA
FREQUENCY (HZ)	60

INPUT / OUTPUT

INPUT	OUTPUT
208 VAC, 1 Φ , 63A	480 VAC, 3 Φ , 15.6A
208 VAC, 3 Φ , 46A	480 VAC, 3 Φ , 20A
240 VAC, 1 Φ , 63A	480 VAC, 3 Φ , 18A
240 VAC, 3 Φ , 40A	480 VAC, 3 Φ , 20A

ENVIRONMENTAL CONDITIONS

OPERATING AMBIENT TEMPERATURE	max 100F
HUMIDITY	non-condensing

OTHER SPECS

CART POWER PLUG TYPE	NEMA 14-50P 
----------------------	---

SAFETY WARNINGS

Only qualified electricians and personnel should service this device
Arc flash explosion hazard
Risk of electric shock
Do not try to lift the smart transformer by the handles
The smart transformer is for indoor use only
Do not cover vents on side or bottom of smart transformer
If the system overheats it will shut down

FOR MORE INFORMATION VISIT
www.sisucinemarobotics.com