

DATASHEET

RID 30 E-SERIES DIESEL GENERATOR 30 KVA



symbolic image



RID 30 E-SERIES S DIESEL GENERATOR 30 KVA



symbolic image



Power rating

Output power	
Power	30 kVA 24 kW
Current	43 A
Voltage	230 / 400 V
Frequency	50 Hz
Power factor	0,8 cos φ

Product overview

Order number open	713669	
Order number closed	713671	
Alternator model	Linz PRO18S C/4	LeroySomer TAL 042 C
Engine type	MITSUBISHI – S4S	
Generator type	synchronous	
Control panel	RID 3000–A	
CE certified in accordance with Machinery Directive 2006/42/EC		

Dimensions and weights Generator

	Length (L)	Width (W)	Height (H)	Weight	Tank
Open	1500 mm	752 mm	1204 mm	650 kg	150 l
Closed	1800 mm	940 mm	1310 mm	790 kg	230 l

Noise level

	1 Meter	4 Meter	7 Meter	10 Meter
Open	89 dB(A)	87 dB(A)	84 dB(A)	81 dB(A)
Closed	76,5 dB(A)	71,5 dB(A)	66,5 dB(A)	63 dB(A)

Fuel consumption

	25% load	50% load	75% load	100% load
Consumption	2,8 l/h	4,3 l/h	6,3 l/h	8,4 l/h

Engine technical data

Engine output	27,6 kW
Engine type	MITSUBISHI – S4S
Engine size	4-Cylinder
Rotational-speed range	1500 u/min
Speed regulation	mechanical
Displacement	3,33 l
Engine w/o cooling system	245 kg

Alternator data

Alternator model	Linz PRO18S C/4	LeroySomer TAL 042 C
Insulation Class	H	
Regulation type	AVR	
Execution	brushless	
Protection class	IP 23	
Airflow Requirement	588 m ³ /h	360 m ³ /h

Intake and exhaust system

Silencer type	industrial
Max. exhaust gas temperature	-
Exhaust gas flow	360 m³/h
Max. exhaust back pressure	67,0 mbar
Air filter type	replaceable element

Engine lubrication

Oil type	RID 10W30
Oil filter type	replaceable element
Total oil volume	10 l
Max. oil temperature	-

Engine cooling

Cooling system	water + air
Cooling system capacity	5,5 l
Fan power consumption	0,7 kW
Cooling air flow	-

Controller RID 3000-A



Functions

Current	Battery voltage	Operating hours counter
Frequency	Power (kVA-kW)	Rotational-speed range
Voltage	Power factor Cosφ.	Fuel level (%)

Commands and other

- Four operating modes: OFF – Manual Start – Automatic Start – Automatic Test
- Push button to force the mains contactor or the generator contactor
- Push buttons: Start/Stop, Error Reset, Up/Down/Side Selection/Enter
- Remote start possible
- Audible alarm
- Protective functions with shutdown
- Engine protection: low fuel level, low oil pressure, high engine temperature
- Generator protection: undervoltage/overvoltage, overload, battery undervoltage/overvoltage, battery charger failure
- Protocols: GSM, Ethernet, Modbus, Canbus