

DATASHEET



RID 15 E-SERIES S RENTAL

DIESEL GENERATOR 15 KVA

symbolic image



Power rating

Output power	
Power	15 kVA 12 kW
Current	21,7 A / 17,3 A
Voltage	230 / 400 V
Frequency	50 Hz
Power factor	0,8 cos φ

Product overview

Order number	712239	
Alternator model	Linz EIX13M F/4	LeroySomer TAL 040 D
Engine type	MITSUBISHI – S4L2	
Generator type	synchronous	
Control panel	RID 3000-A	
CE certified in accordance with Machinery Directive 2006/42/EC		

Dimensions and weights Generator

	Length (L)	Width (W)	Height (H)	Weight	Tank
Dimensions	2020 mm	980 mm	1635 mm	745 kg	170 l

Noise level

	1 Meter	4 Meter	7 Meter	10 Meter
Noise level	65 dB(A)	62 dB(A)	59 dB(A)	57 dB(A)

Fuel consumption

	25% load	50% load	75% load	100% load
Consumption	1,9 l/h	2,6 l/h	3,45 l/h	4,4 l/h

Engine technical data

Engine output	14,5 kW
Engine type	MITSUBISHI - S4L2
Engine size	4-Cylinder, in-line
Rotational-speed range	1500 u/min
Speed regulation	mechanical
Displacement	1,76 l
Engine w/o cooling system	160 kg

Alternator data

Alternator model	Linz E1X13M F/4	LeroySomer TAL 040 D
Insulation Class	H	
Regulation type	AVR	
Execution	brushless	
Protection class	IP 23	
Airflow Requirement	270 m³/h	216 m³/h

Intake and exhaust system

Silencer type	industrial
Max. exhaust gas temperature	-
Exhaust gas flow	234 m³/h
Max. exhaust back pressure	65,0 mbar
Air filter type	replaceable element

Engine lubrication

Oil type	RID 10W30
Oil filter type	replaceable element
Total oil volume	6,0 l
Max. oil temperature	135 °C

Engine cooling

Cooling system	water + air
Cooling system capacity	4,9 l
Fan power consumption	0,6 kW
Cooling air flow	-

Controller RID 3000-A



Functions

Current	Battery voltage	Operating hours counter
Frequency	Power (kVA-kW)	Rotational-speed range
Voltage	Power factor Cosφ.	Fuel level (%)

Commands and other

- Four operating modes: OFF – Manual Start – Automatic Start – Automatic Test
- Push button to force the mains contactor or the generator contactor
- Push buttons: Start/Stop, Error Reset, Up/Down/Side Selection/Enter
- Remote start possible
- Audible alarm
- Protective functions with shutdown
- Engine protection: low fuel level, low oil pressure, high engine temperature
- Generator protection: undervoltage/overvoltage, overload, battery undervoltage/overvoltage, battery charger failure
- Protocols: GSM, Ethernet, Modbus, Canbus