

### Long Term Storage Recommended Procedure checklist:

- Move the refuge chamber to a clean, dry area.
- It is preferable to have the refuge chamber undercover, if this is not possible consider covering with tarps as direct sun can damage all the external decals.
- Air conditioner can remain off but the controller should be left on.
- Keep front door locked to avoid theft or tampering.
- If power is available then connect refuge chamber to mains power to ensure batteries are kept at full charge and healthy.
- If power is not available then all batteries should be completely disconnected to minimise natural drain.
- Too optimise battery longevity. If storage location is in extreme weather conditioners ie. above 30c or below -10c , then remove the batteries and store in an area with better conditions. Ie Warehouse.
- If batteries have been disconnected then they should be connected to a battery charger every 3 months to ensure they stayed fully charged as they will naturally drain without use.

*For further information please call MineARC Systems on +61 8 9333 4990 (AWST GMT+8:00)*