

# RollerMouse Red Plus

*Wireless*

Product  
Manual




Contour

## What's in the Box?

1. RollerMouse Red
2. Wrist rest
3. Wrist rest removal key
4. Keyboard risers (short and long version assembled in box)
5. Dongle
6. USB extender
7. Charging cable



## User guide



## Functions

- A. Rollerbar
- B. Cursor speed
- C. Copy
- D. Paste
- E. Left-click
- F. Right-click
- G. Scroll wheel
- H. Double-click
- I. On/off switch
- J. Dongle storage
- K. Wrist rest removal slot



## Quick start

### 1. Connect via Bluetooth

Power on the RollerMouse (button I). On your computer, navigate to the area of settings regarding Bluetooth connections. Select the option to add or discover a Bluetooth device. Your RollerMouse will automatically be recognized, select it for the computer to start Bluetooth connection.

### 2. Connect via USB dongle

Insert the USB dongle into an available USB port and power on your RollerMouse. Your computer will recognize your new device and connect automatically.

### 3. Connect via wired USB connection

Connect the USB cable to your RollerMouse and into an available USB port on your computer. Your computer will recognize your new device and connect automatically.

## Using the Rollerbar

The Rollerbar provides two functions:


- Moving the Rollerbar from side to side and up/down performs cursor movement.
- Pressing down on the Rollerbar performs a left click.

## Battery level

Your RollerMouse has a built-in rechargeable battery and comes pre-charged with an expected battery life of up to 3 months with average daily use.

To see the battery level, press the cursor speed button once. The RollerMouse will first display the current cursor speed (DPI), then display the current battery level.

If your RollerMouse Red is running low on battery, the center LED light will start blinking red.




## Charging

To charge your RollerMouse remove the USB extender and dongle from the charging cable. Plug the cable into the RollerMouse and connect to your computer. Your RollerMouse will be fully charged in approx. 6 hours. You may continue to use the RollerMouse as it charges.

## Cursor Speed (DPI)

Press the Cursor speed (button **B**) to cycle through cursor speeds. There are speed selections which range from slow (600 DPI) to fast (2800 DPI). Speed can be identified by the LED lights as shown.



## Rollerbar click force adjustment

Click force refers to the level of resistance when clicking the Rollerbar. To adjust click force, press and hold button **B** (Cursor speed) then press and release **A** (Rollerbar). Move button **G** (Scroll wheel) up/down to adjust the click force and release button **B** to confirm.

To disable the Rollerbar click function, adjust until all LEDs are illuminated.



## Rollerbar click volume adjustment

The Rollerbar has 6 different click volume settings. To change the click volume, press and hold button **B** (Cursor speed) then press and release button **G** (Scroll wheel), the LED light will show the current click volume setting. To adjust the click volume move button **G** up/down and then release button **B** to confirm.

To disable the Rollerbar click volume, adjust until all LEDs are illuminated.





## Pairing and secondary options

1. Restart Bluetooth pairing:  
Press button **B**. While continuing to hold **B**, press and release button **E** two times, then release button **B**.
2. Select Bluetooth-only connectivity:  
Press button **B**. While continuing to hold **B**, press and release button **E** three times, then release button **B**.
3. Select dongle-only connectivity:  
Press button **B**, while continuing to hold **B**, press and release button **F** three times, then release button **B**.
4. Restore pairing with dongle:  
Unplug then re-plug the dongle to the unit to enable pairing. Hold the device close to dongle and press button **B**. While continuing to hold **B**, press and release button **F** two times, then release button **B**.
5. Reset wireless function to automatic pairing mode:  
Press button **B**. While continuing to hold **B**, press and release button **E**, then release button **B**.


When the device is plugged with the USB cable, this connection overrides wireless connectivity.

Please visit [contourdesign.com/BT](http://contourdesign.com/BT) for further information about Bluetooth.




## Operating system

RollerMouse has different modes to best fit your operating system.

Press and hold both button **B** (Cursor speed) and button **D** (Paste) for two seconds, then the LED light will show the respective mode. While continuing to hold button **B**, release button **D** and click button **D** to toggle through the different modes. Release both buttons to select the desired mode.



## Mode settings

<b>PC mode</b>		Windows
<b>Mac mode</b>		OS
<b>HID mode</b>		Linux



## Keyboard positioning

Before using your RollerMouse, please take a moment to adjust your keyboard.

If you are using other keyboards than Contour's Balance Keyboard – designed specifically for RollerMouse – you can use the keyboard risers to achieve the desired keyboard height and angle.

The spacebar on your keyboard should come just above your Rollerbar. Fit the end of the keyboard risers into the slot on the back of the RollerMouse – then place the keyboard as it was lying on the table.

For a proper ergonomic position the front edge of the keyboard should be as close to the Rollerbar as possible. We recommend to use negative tilt helping you to hold a neutral wrist position and decreasing the extension of your fingers.



Negative tilt




Neutral elevated



Neutral flat



Positive tilt




*Note: The short keyboard riser is attached to the longer version in the box. To use it separately, pull it upwards following the direction of the arrow.*




## Software driver

All Contour's ergonomic products are plug-and-play. If you want to customize your RollerMouse, we recommend to download the free driver available at:

[contourdesign.com/drivers](https://contourdesign.com/drivers)



## Battery disposal



# Contour

## Contour Design Nordic A/S

Nyropsgade 41-43, 1. floor  
DK-1602 Copenhagen V, Denmark  
Phone: +45 70 27 02 27  
Email: [info@contourdesign.com](mailto:info@contourdesign.com)

## Contour Design, Inc.

10 Industrial Drive  
Windham, New Hampshire 03087, USA  
Phone: (603) 893-4556  
Email: [ergoinfo@contourdesign.com](mailto:ergoinfo@contourdesign.com)

For more information please visit:  
[www.contourdesign.com](http://www.contourdesign.com)

Tested to comply with FCC and  
IC standards.



### FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules.

Operation is subject to the following two conditions

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

### IC Statement

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:

1. This device may not cause interference; and
2. This device must accept any interference, including interference that may cause undesired operation of the device.

The term "IC:" before the certification/registration number only signifies that the Industry Canada technical specifications were met. This product meets the applicable Industry Canada technical specifications.

### Warranty

If there is a functional defect due to faulty manufacturing, we will replace the product. This warranty does not cover damage that results from misuse of the product.

### Attention!

If you attempt to dismantle your RollerMouse you will invalidate your warranty.