

## BL-70XF0-BW | BL-70XF0-KW INSTRUCTIONS

Thank you for your purchase of this indoor/outdoor rated table lamp. Designed to integrate seamlessly into your home décor, this light also offers the convenience of battery powered operation for use around the house. Perfect for ambient lighting for dinner, deck parties, lake life, reading and more, these Amerelle lamps are as stylish as they are functional.



BL-70XF0-BW



BL-70XF0-KW

### Key Features:

- IP54 rating for weathertightness – dust and rain tight for light outdoor use
- Li-Ion rechargeable batteries with USB-C connector
- Adjustable white color temperatures
- “Insect Mask” – a 1700K warm color temperature that is invisible to moths and other flying insects that are otherwise attracted to light
- A Color Temperature Lock, ideal for use when multiple lamps are in use and a consistent color temperature is desired.

### CAUTION

- Do not disassemble or modify the product.
- Do not look directly at the LED light source when lighting.
- Please disconnect the USB cable when the product will not be used for a long time.
- Use and store product between 32 Degrees and 104 Degrees F
- Do not leave the product outdoors for an extended period to avoid damage from weather and strong sunlight.
- To clean the lamp, wipe with a soft and dry cloth.

### General Operation:

- To turn on the lamp quick tap the power button (⏻) located on the top of the shade.
- Continuously tap the power button (⏻) to cycle through color temperatures 1700K > 3000K > 5000K > OFF (Fig. 1)
- Press and hold the power button (⏻) after to dim the light. The light will stop at its maximum and minimum brightness. Release and repeat to continue adjusting as needed. (Fig. 2)
- After 15 seconds of no button press, a single tap will power off the light. The light will return to its last used brightness when powered back on and can be adjusted per Step 2 and 3 above.

FIGURE 01





FIGURE 02



Color Temperature Lock:

- 1. While the lamp is OFF, press and hold down the power button for 5 seconds until the lamp starts flashing.
- 2. Tap the power button to select the color temperature you want to lock to. The flashing color will indicate the color that the light will lock to, 1700K > 3000K > 5000K > All Colors (Lock Disabled).
- 3. After 5 seconds of no tapping, the current state will be saved, and the light will turn on either to the locked color or to 1700K if the lock is disabled.
- 4. In CCT Lock mode, the General Operation instructions for changing color temperature (Step 2) will not function, however the dimming feature (Step 3) will operate normally.

To remove the color temperature lock:

- 1. While the lamp is turned off, hold down the power button for 5 seconds.
- 2. Tap the power button until your reach the setting where all three-color temperatures flash. After 5 seconds of no button presses, the lamp will disable color temperature lock mode and turn on at 1700K. It may now be operated normally per the General Operation instructions.

Battery Maintenance and Charging:

**NOTE:** FULLY CHARGE LAMP BEFORE INITIAL USE

**Charging:**

To charge your lamp, connect the included power cord into the lamp’s USB-C port on the underside of the lamp shade. The light near the charging port will turn red when charging is in process. Charging is complete when the indicator light turns off.

**Extended Storage:**

To achieve optimum battery longevity when the lamp will not be used for an extended period (>1 month), keep the charge between 20% and 80%. It is advised to regularly charge/discharge the product to maintain this level. A rule of thumb to get to 80% is to charge the lamp fully then operate at full brightness for two hours.

**WARNING:** Do not disassemble or modify this light. Modification voids the manufacturer’s warranty and any applicable regulatory certifications this light may possess.

**⚠ WARNING:** This product can expose you to chemicals including lead and phthalates, which are known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

| Product SKU | Height   | Max Lumens | Color Temperature   | Run Time  | Charge Time | Battery Capacity | IP Rating |
|-------------|----------|------------|---------------------|-----------|-------------|------------------|-----------|
| BL-70XFO-BW | 11.3 in. | 200 lm     | 1700K, 3000K, 5000K | 28+ Hours | 8 -9 Hours  | 5200 mAh         | IP54      |
| BL-70XFO-KW |          |            |                     |           |             |                  |           |



MILWAUKEE, WI  
CUSTOMER SERVICE: 800-527-0195  
AMERTAC.COM  
MADE IN CHINA  
© 2025 AMERICAN TACK & HARDWARE™

**Limited Warranty**

Under normal use and conditions, American Tack and Hardware provides to the original purchaser of this product a one year limited express warranty that is set forth in the Limited Warranty stated in full at [www.amertac.com/warranties](http://www.amertac.com/warranties). The Limited Warranty is in lieu of all other express or implied warranties or liabilities subject to the exceptions explained fully in the Limited Warranty on the website.