

# DATASHEET

## RS 3001 P PETROL GENERATOR 3 KVA

*symbolic image*



## Power rating

| Output power |                 |
|--------------|-----------------|
| Power        | 3,0 kVA         |
| Current      | 13 A            |
| Voltage      | 230 V           |
| Frequency    | 50 Hz           |
| Power factor | 1 cos $\varphi$ |

## Product overview

|  |                          |
|--|--------------------------|
| Order number   | 717067                   |
| Engine type  | BRIGGS & STRATTON 6,5 HP |
| Engine size  | 1-Cylinder               |
| Generator type   | synchronous              |
| Protection class   | IP 23                    |
| CE certified in accordance with Machinery Directive 2006/42/EC |                          |

### Engine technical data

|                          |                |
|--------------------------|----------------|
| Rotational-speed range   | 3000 u/min     |
| Fuel type                | Petrol 92 / 95 |
| Oil                      | 5W30           |
| Oil volume in the engine | 0,6 l          |
| Engine power             | 4,1 kW         |
| Cooling system           | Air            |
| Starter                  | Manual         |

### Dimensions and weights Generator

|            | Length (L) | Width (W) | Height (H) | Weight | Tank |
|------------|------------|-----------|------------|--------|------|
| Dimensions | 770 mm     | 565 mm    | 593 mm     | 55 kg  | 10 l |

### Noise level

|             |          |
|-------------|----------|
| Noise level | 67 dB(A) |
|-------------|----------|

### Fuel consumption

|             |           |
|-------------|-----------|
|             | 100% load |
| Consumption | 1,0 l/h   |