

 English



Series S  
heating device

Heat Your Own Technology®

User guide

# Congratulations!

In just a few moments, you will begin to enjoy the ARKX Heat-Your-Own® experience.

This guide provides the necessary information to use your new ARKX Series S device.

## Safety and precautions

- The device is not designed to be opened by unqualified personnel.
- Do not operate the device while it is connected to the charger.
- Avoid prolonged exposure of the device to extreme temperatures.
- Do not charge the battery at temperatures below 0°C.
- If the temperature exceeds 40°C, do not charge the battery to 100%.
- **Keep out of reach of minors.**

## Battery charging

- Use the provided cable with a 5V USB-C charger with a minimum current of 2A.
- Fully charge the battery before using the device for the first time.
- When all three LEDs are lit in white, the battery is fully charged.
- External batteries (power banks) can be used to charge the device.

## How to Use Your ARKx Series S

The ARKX experience is customizable. In addition to choosing flavors, you can adjust the temperature and experiment with different amounts of tobacco. We recommend starting with a medium temperature and not overfilling the chamber. The temperature can be adjusted during sessions.

## •Step 1

- Remove the mouthpiece and load the chamber. Leave 2 to 3 mm of empty space from the top edge to ensure the mouthpiece closes properly.

## •Step 2

- To turn on the device, quickly press the power button five times within two seconds. The LEDs will flash in the color of the last selected temperature. Once heating is complete (in approximately 20 seconds), the LEDs will turn white and stop flashing. The device will vibrate, indicating it is ready for use. The number of illuminated LEDs indicates the battery charge level. If the battery charge is too low for operation, all three LEDs will light up in the selected temperature color, then turn white and flash before the device shuts off.

## •Step 3

- During use, the LEDs remain white. To check the current operating temperature, press the button once. The LEDs will change to the selected temperature color and then return to white: **Azul** 196°C **Verde** 205°C **Rajo** 215°C
- To change the temperature, press the button three times. Press it three times again until the LEDs display the desired temperature color.
- To stop or restart heating, press the button for 2 seconds, release it, and wait for the device to vibrate.

## •Step 4

- The device will automatically turn off after 5 minutes. If you wish to turn it off earlier, quickly press the power button five times within two seconds.



## Cleaning

- Residue in the chamber and filter can be removed using the brush. For deep cleaning, remove the mouthpiece, filter cap, and filter, soak them in isopropyl alcohol for 5 minutes, and then rinse with fresh water. Wait until all components are completely dry before reinstalling them.

## Warranty

This product is guaranteed against manufacturing defects. If service is required, contact the authorized distributor in your market for information about warranty terms and procedures. Warranty conditions may vary by region.



[www.arkxway.com](http://www.arkxway.com)