

MAINS DISTRIBUTION UNITS

MDU10-C-B-001 | CHANGEOVER & MCB



To obtain a quote:
Call: +44 (0)1724 273224
Email: sales@dem-uk.com

- Input Protected by 16Amp Merlin Gerin MCB's
- Automatic and Fast Changeover
- 2 PowerCon Input Connectors
- 10 Individually Fused IEC Outlets
- Red LED Fuse Failure Indication
- Power Present Indicator
- 16 Amp Max Total Load
- 6 Amp Max Load Per Output
- 230VAC 50Hz



OVERVIEW - The unit safeguards equipment from primary mains supply failure. It is housed in a sturdy 19" 1RU rack mounted enclosure, 195mm behind panel depth (300mm including lacing bar) and includes a wide clip-on designation strip for clear marking.

FEATURES - In normal operation the outputs are supplied from the primary supply. If the primary supply fails the relay switches to the secondary supply. The relay switches at ~20ms and the small glitch on the mains supply is dealt with by the power supplies in the powered equipment. The result is that the units remain powered without problems. This is especially true of any computers connected to the MDU. The two mains supplies may be independent but must be of the same phase.

On the return of the primary supply, the unit will switch back to primary power, again without issues. The unit is designed for total power loss.

FINISH - The front panel comes in a standard semi-gloss black finish (RAL9005)

All Products in the Mains Distribution Range	
Product Code	Description
MDU10-N-B-001	10 Output Mains Distribution Unit with MCB
MDU10-C-B-001	10 Output Changeover Mains Distribution Unit with MCB
MDU12-S-C-001	12 Output Changeover Mains Distribution Unit with Sequential Start
MDU12-32-SN-001	12 Output Mains Distribution Unit 32amp Inlet with Switch
MDU12-32-BN-001	12 Output Mains Distribution Unit 32amp Inlet with Breaker
MDU14-C-N-001	14 Output Changeover Mains Distribution Unit with Switch
MDU14-C-N-002	14 Output Changeover Mains Distribution Unit with Indicator
MDU14-C-M-001	14 Output Changeover Mains Distribution Unit with Switch
MDU14-C-M-002	14 Output Changeover Mains Distribution Unit with Indicator
MDU14-N-S-001	14 Output Mains Distribution Unit, 2 x Inputs, 2 x 7 Outputs
MDU14F10	14 Output Filtered Mains Distribution Unit 10amp Inlet
MDU14F16	14 Output Filtered Mains Distribution Unit 16amp Inlet