

# MAINS DISTRIBUTION UNITS

## MDU14-N-S-001 | 2 INPUTS



To obtain a quote:  
Call: +44 (0)1724 273224  
Email: sales@dem-uk.com

- 2 x 10 Amp Inputs (10amp max per input)
- 14 Individually Fused IEC Outputs
- 2 PowerCon Input Connectors
- Fuse Live Indication
- 6 Amp Max Load Per Output
- 115-230VAC 50Hz



**OVERVIEW** - The MDU14-N-S-001 is designed to meet the current trend of increasing the number of separately powered units in a rack frame. The functional packing density of the latest broadcast equipment continues to increase. Although the overall power needs have decreased, the number of separate pieces of equipment per rack has increased as more functionality has been packed into smaller rack-mounted enclosures. Potentially, the power need per rack unit has increased.

**FEATURES** - This unit is housed in a sturdy 19" 1RU rack mounted enclosure, 195mm behind panel depth (300mm including lacing bar). Each individually fused output is capable of 6 Amps maximum (subject to total maximum of 20 Amps). Green indicators warn fuse live for quick and easy identification of output condition. The units are provided with a sturdy yet compact cable-tie arrangement. The unit is supplied with a designation strip fitted at no extra charge, though this may be omitted at the ordering stage if required.

**FINISH** - The front panel comes in a standard semi-gloss black finish (RAL9005).

All Products in the Mains Distribution Range	
Product Code	Description
MDU10-N-B-001	10 Output Mains Distribution Unit with MCB
MDU10-C-B-001	10 Output Changeover Mains Distribution Unit with MCB
MDU12-S-C-001	12 Output Changeover Mains Distribution Unit with Sequential Start
MDU12-32-SN-001	12 Output Mains Distribution Unit 32amp Inlet with Switch
MDU12-32-BN-001	12 Output Mains Distribution Unit 32amp Inlet with Breaker
MDU14-C-N-001	14 Output Changeover Mains Distribution Unit with Switch
MDU14-C-N-002	14 Output Changeover Mains Distribution Unit with Indicator
MDU14-C-M-001	14 Output Changeover Mains Distribution Unit with Switch
MDU14-C-M-002	14 Output Changeover Mains Distribution Unit with Indicator
MDU14-N-S-001	14 Output Mains Distribution Unit, 2 x Inputs, 2 x 7 Outputs
MDU14F10	14 Output Filtered Mains Distribution Unit 10amp Inlet
MDU14F16	14 Output Filtered Mains Distribution Unit 16amp Inlet