

• YOUR
• SMART
• ENERGY



Backup Box - PLUS



BASISGEGEVENS

Automatische netontkoppeling bij stroomuitval

Slimme belastingsturing

Herverbinding met het net na stroomuitval

Ingebouwde energiemeter

Backup Box - PLUS



Compatibele opslagsystemen	SMILE-B3/5/T10, SMILE-S6-HV, SMILE-T10-HV, SMILE-G3-S5, SMILE-G3-T4/T5/T6/T8/T10, SMILE-G3-T12/T15/T20
Scherm	LCD
Interface	RS-485
Bedrijfstemperatuur	-10 °C ~ 50 °C
Luchtvochtigheid	15% ~ 85%
IP-beschermingsklasse	IP21
Afmetingen (B x H x D)	410 x 605 x 169.2 mm
Productgarantie	5 jaar
Netspanningsbereik	184 V - 264.5 V (L-N)
Netfrequentie	50 / 60 Hz
Maximale in-/uitgangsstroom	63 A / 63 A / 63 A
Nettogewicht	17.6 kg



Alpha ESS Co., Ltd.

+86 513 8060 6891
info@alpha-ess.com
www.alphaess.com
No. 1086, Bihua Road,
Nantong Hi-Tech Zone,
Jiangsu Province, China

Alpha ESS Italy S.r.l.

+39 339 462 4288
info@alphaess.it
www.alphaess.com
Via Del Molinuzzo 83,
59100 Prato (PO), Italy

Alpha ESS Europe GmbH

+49 610 3459 1601
europe@alpha-ess.de
www.alphaess.de
Horizon Tower 17.0G
Alfred-Herrhausen-Allee 3-5
65760 Eschborn, Germany

Alpha ESS UK Ltd.

+44 0330 043 2610
info@alpha-ess.com
Drake house, Long street,
Dursley, GL11 4HH UK

Alpha ESS Australia Pty. Ltd.

+61 02 9000 7676
techsupport@alphaess.au
www.alphaess.com
8/15-21 Gibbes Street,
Chatswood,
NSW 2067 Australia

Alpha ESS USA, Inc.

+1 408 368 7828
usa@alpha-ess.com
Unit 5 2180 S Ivanhoe St,
Denver, CO 80222 USA

Alpha ESS International Pte. Ltd.

+65 6513 1125 / +65 6513 1126
Singapore@alpha-ess.com
2 Corporation Road #01-06A
Corporation Place 618494
Singapore

Alpha ESS Korea Co., Ltd.

info@alpha-ess.com
2F, 19-4, Nohyeong 11-gil,
Jeju-si, Jeju-do, Republic
of Korea

Alpha ESS Benelux B.V.

contact@alphaess.nl
www.alphaess.nl
High Tech Campus 41, 5656AE
Eindhoven, Netherlands

Alpha ESS South Africa (Pty.) Ltd.

measervice@alpha-ess.com
La Rocca Office Park, Block
B1 321 Main Road, Bryanston,
Johannesburg, 2191